



GV2-ME



GV2



GV3



AE

AD

AS

GV series Motor protection Circuit Breaker are mainly used for the overload and short circuit protection of the motor in AC 50/60Hz. 0.1-80A power circuit, as a full-voltage starter to start and cut off the motor, under the AC3 load or for the overload and short circuit protection of the circuit and power equipment in the power distribution network.

Specification

Type	Rated standard power of 3-phase motors 50/60Hz in category AC-3						Setting range (A)
	220V	380V	415V	440V	500V	660V	
	KW	KW	KW	KW	KW	KW	
GV2-M01	--	--	--	--	--	--	0.1-0.16
GV2-M02	--	--	--	--	--	--	0.16-0.25
GV2-M03	--	--	--	--	--	--	0.25-0.4
GV2-M04	--	--	--	--	--	0.37	0.4-0.63
GV2-M05	--	--	--	0.37	0.37	0.55	0.63-1
GV2-M06	--	0.37	--	0.55	0.75	1.1	1-1.6
GV2-M07	0.37	0.75	0.75	1.1	1.1	1.5	1.6-2.5
GV2-M08	0.75	1.5	1.5	1.5	2.2	3	2.5-4
GV2-M10	1.1	2.2	2.2	3	3.7	4	4-6.3
GV2-M14	2.2	4	4	4	5.5	7.5	6-10
GV2-M16	3	5.5	5.5	7.5	7.5	9	9-14
GV2-M20	4	7.5	9	9	9	11	13-18
GV2-M21	5.5	11	11	11	11	15	17-23
GV2-M22	5.5	11	11	11	15	18.5	20-25
GV2-M32	7.5	15	15	15	18.5	26	24-32
GV3-M06	--	0.37	--	0.55	0.75	1.1	1-1.6
GV3-M07	0.37	0.75	1.1	1.1	1.1	1.5	1.6-2.5
GV3-M08	0.75	1.5	1.5	1.5	2.2	3	2.5-4
GV3-M10	1.1	2.2	2.2	3	3.7	4	4-6
GV3-M14	2.2	4	4	4	5.5	7.5	6-10
GV3-M20	4	7.5	7.5	7.5	10	11	10-16
GV3-M25	5.5	11	11	11	15	18.5	16-25
GV3-M40	11	18.5	22	22	25	33	25-40
GV3-M63	15	30	33	33	40	55	40-63
GV3-M80	22	40	45	45	55	63	56-80

Moulded Case
Circuit Breaker